


Notes:

1. MAIN DISCONNECT PROVIDED BY OTHER.
2. FIELD WIRING TO BE COPPER RATED FOR 75°C MINIMUM.
3. - - - - INDICATES FIELD WIRING OUTSIDE OF CABINET.
4. AUXILIARY CONTACTS LIST AND OPERATION NOTES ON SHEET 3.
5. THE AMPACITY OF CONDUCTORS SUPPLYING THE CONTROL PANEL TO BE ROUNDED UP TO THE NEXT SIZE LARGER STANDARD WIRE GAUGE.
6. MOP VALUES TO BE ROUNDED DOWN TO THE NEAREST STANDARD RATING OF THE OVERCURRENT PROTECTION DEVICE.
7. SHORT CIRCUIT CURRENT RATING (SCCR): 65 kA



MINIMUM CIRCUIT AMPACITY (MCA)

SYSTEM HP	208 V	230 V	460 V
7.5 HP	106.4 AMPS	96.7 AMPS	48.8 AMPS
10 HP	134.4 AMPS	122.2 AMPS	61.6 AMPS

MAXIMUM OVERCURRENT PROTECTION (MOP)

SYSTEM HP	208 V	230 V	460 V
7.5 HP	127.1 AMPS	115.5 AMPS	57.8 AMPS
10 HP	161.7 AMPS	147.0 AMPS	73.5 AMPS

QUADRUPLEX SYSTEM FULL LOAD AMPERES

SYSTEM HP	208 V	230 V	460 V
7.5 HP	86.8 AMPS	80.9 AMPS	40.8 AMPS
10 HP	116.8 AMPS	105.7 AMPS	53.2 AMPS

INDIVIDUAL FULL LOAD AMPERES

SYSTEM HP	208 V	230 V	460 V
7.5 HP	21.0 AMPS	19.6 AMPS	9.8 AMPS
10 HP	28.5 AMPS	25.8 AMPS	12.9 AMPS

FUSE SELECTION CHART (MAX FUSE SIZES SHOWN)

SYSTEM HP	FUSES	208 V	230 V	460 V
7.5 HP	FL1/FL2/FL3	---	---	50 AMPS
10 HP		---	---	60 AMPS
ALL	F1/F2/F4/F5/F7/FB/F10/F11	6.0 AMPS	6.0 AMPS	6.0 AMPS
	F3/F6/F9/F12	---	---	6.0 AMPS
	F21-F24	2.5 AMPS	2.5 AMPS	2.5 AMPS
	F33	1.0 AMP	1.0 AMP	1.0 AMP
	F35	0.5 AMP	0.5 AMP	0.5 AMP

FL1/FL2/FL3 ARE LITTELFUSE JTD 600V TYPE
 F1-F12 ARE LITTELFUSE KLDL 600V TYPE
 F21-F24/F33/F35 ARE LITTELFUSE 2AG 250V TYPE

RELIEF VALVE SETTINGS ("HgV)


ALTITUDE	7.5HP	8.6HP
0-1000'	21.5	23
1001-2000'	20.5	22
2001-3000'	19.5	21
3001-4000'	18.5	20
>4000'	CONSULT FACTORY	

DEFAULT VACUUM SETTINGS ("HgV)

ALTITUDE	LEAD CUT-OFF	LAG CUT-ON	MAXIMUM LIMITS	MINIMUM LIMITS
0-1000'	21	16	25 18	21 16
1001-2000'	20	16	24 18	21 16
2001-3000'	19	16	23 18	21 16
3001-4000'	18	16	22 18	21 16
>4,000'	CONSULT FACTORY			

BACKUP VACUUM SWITCH ("HgV)

BVS-1	CUT-ON	15
-------	--------	----




PUMP PCB JUMPER/SWT SETTINGS

JPR/SWT	POSITION
JP1	1-2
S1	A (AUTO)

Revised: _____ Date: _____ Drawn: MDB Date: 10/30/18
 Scale: NTS
D
 Description: DWG WIRING CONTROL QX DRY VAC 7.5-10HP 208-460/3/60, 65kA
 Part Number: 4107 8568 42
 Rev: HOP 180863 Rev: 00
 Sheet 1 of 3 DO NOT SCALE THIS DOCUMENT

Notes:

1. FIELD WIRING TO BE COPPER RATED FOR 75°C MINIMUM.
2. - - - - - INDICATES FIELD WIRING OUTSIDE OF CABINET.





PUMP PCB JUMPER/SWT SETTINGS

JPR/SWT	POSITION
JP1	1-2
S1	A (AUTO)

Revised:	Date:	Drawn:	MDB	Date:	10/30/18
		<small>This drawing and the information contained herein remain the property of BeaconMedas and may not be used for other than the purpose for which it is issued without the express written permission from BeaconMedas Engineering.</small>			
Description: DWG WIRING CONTROL QX DRY VAC 7.5-10HP 208-460/3/60, 65kA		Part Number: 4107 8568 42 Rev: 00 Sheet 2 of 3			
Scale: NTS		D <small>DO NOT SCALE THIS DOCUMENT</small>			

Notes:

1. FIELD WIRING TO BE COPPER RATED FOR 75°C MINIMUM.
2. - - - - - INDICATES FIELD WIRING OUTSIDE OF CABINET.



AUTO OPERATION:

THE MASTER PCB WILL CONTROL THE ADAPTIVE FUNCTIONALITY OF THE SYSTEM. THE ADAPTIVE CONTROL CAUSES THE VACUUM PUMPS TO START BASED ON THE VACUUM LEVEL. THE SIGNAL TO STOP IS BASED ON THE LENGTH OF TIME THE VACUUM SYSTEM WAS NOT RUNNING. THE MASTER PCB DETERMINES THE MINIMUM RUN TIME OF A PUMP ONCE IT HAS STOPPED. IF THE VACUUM SYSTEM IS STOPPED FOR A LONG PERIOD OF TIME, THE MINIMUM RUN TIME AFTER A RESTART WILL BE SHORT. IF THE VACUUM SYSTEM IS STOPPED FOR A SHORT PERIOD OF TIME, THE MINIMUM RUN TIME WILL BE LONGER. SEE O&M MANUAL FOR SPECIFIC VARIATIONS. IF DURING OPERATION THE FOURTH VACUUM PUMP IS REQUIRED TO TURN ON, THE MASTER CONTROLLER WILL SET A LAG ALARM CONDITION.

PUMP PCB S1 POSITION:

POSITION (A) - AUTO (DEFAULT):

THE PUMP WILL OPERATE NORMALLY AS DESCRIBED ABOVE IN "AUTO OPERATION".

POSITION (X) - OFF:


THE PUMP IS DISABLED FROM RUNNING.

POSITION (O) - MANUAL:

THE PUMP WILL RUN CONTINUOUSLY.

PCB FAULT:

IF A PUMP PCB ETHERNET FAULT OR A TRANSDUCER FAULT OCCURS, THE PUMP PCB WILL AUTOMATICALLY SWITCH TO MANUAL MODE. VACUUM PUMPS WILL START WHEN BVS-1 (BACKUP VACUUM SWITCH) CLOSSES AND STOP WHEN IT OPENS. COMPRESSORS WILL NOT SEQUENCE IN THIS CONDITION AND CAN OPERATE UNTIL THE ETHERNET OR TRANSDUCER FAULT IS REPAIRED.



NOTE:
AUXILIARY CONTACTS 965-972 ARE "CLASS 1 CONTROL CIRCUITS. USE CLASS 1 CONDUCTORS."

AUX CONTACTS ARE RATED 0.7A_{dc}/0.7A_{rms} @ 24V MAX. UNLESS OTHERWISE NOTED.

AUX CONTACTS CLOSED DURING NORMAL OPERATION.

Revised:	Date:	Drawn:	MDB	Date:	10/30/18
<small>This drawing and the information contained herein is the property of Beacomedas and may not be used for other than the purpose for which it is issued without the expressed written permission from Beacomedas Engineering.</small>					
BEACOMEDAS				D	
Description: DWG WIRING CONTROL QX DRY VAC 7.5-10HP 208-480/3/60, 65KA		Part Number: 4107 8568 42			
DR: HOP 180863		Rev: 00		Scale: NTS	
Sheet 3 of 3		DO NOT SCALE THIS DOCUMENT			